

PUBLIC SAFETY ULTRA COMPACT SIGNAL BOOSTERS

764 - 869 MHz • Class B

C720
CS20

Product Features

- IF SAW filtering, sharp filtering response, outstanding out of band rejection
- Alarm outputs via LEDs
- Output power meter
- User adjustable gain control, UL and DL independent
- Automatic Gain Control, UL and DL independent



Ultra Compact Signal Booster

Applications

- Indoor coverage extension
- Passive DAS systems
- Leaky cable network
- Fixed and mobile applications



Specification

Value

Type	Ultra Compact Band Selective Signal Booster
Frequency range	C720-xx: 764-776 / 794-806 MHz CS20-xx: 806-824 / 851-869 MHz
Passband BW. min	3 MHz to Full Band, factory adjusted
Center Frequency calibration	Via software (not available for Full Band versions)
Gain, maximum	65dB
Passband ripple	+/- 2.5 dB
Gain, manual control	18dB range, digitally controlled in 3dB steps
AGC range	0 to 20 dB min
Composite output power, DL	+ 20 dBm
Composite output power, UL	+ 20 dBm
IM generation	< -13dBm
Noise figure	6.0 dB max at maximum output power
Impedance	50 Ω
Connectors	SMA(f) as standard
Control	Local, via USB
AC Supply	110/220 VAC 50/60 Hz 20W
Housing	IP24
Temperature range	-22° to 140° F • -30° to +60° C
Dimensions	7.9 x 5.9 x 1.2 inches • 200 x 150 x 30 mm
Weight	3.3 lbs • 1.5 kg
Mounting	Wall mounting as standard
Heat dissipation	Natural convection
MTBF	>100.000 hours

DOC BD282.01 - 26112015
 Fiplex is a registered trademark of Fiplex Communications, Inc.
 Fiplex Communications, Inc. reserves the right to change specifications without prior notice.

WARNING: This is NOT a CONSUMER device. It is designed for installation by FCC LICENSEES and QUALIFIED INSTALLERS. You MUST have an FCC LICENCE or express consent of an FCC Licensee to operate this device. Unauthorized use may result in significant forfeiture penalties, including penalties in excess of \$100,000 for each continuing violation.