# VHF DIGITAL SIGNAL BOOSTERS 155 - 174 MHz

# DH124-040 DH124-041

### **Product Features**

- Channel Selective, software programmable
- Fully digital signal boosters, FPGA based
- Auto diagnostic
- Uplink squelch, per channel and per time slot
- User adjustable gain control, UL and DL independent, per channel
- Automatic Gain Control, per channel and per time slot
- Weatherproof enclosure, IP67/NEMA4X
- NFPA compliant
- · Built in spectrum analyzer



## **Applications**

- Indoor coverage: tunnels and mobile fast-deploy communication units
- $\bullet$  Outdoor coverage: oil rigs, stadiums, dense urban areas, rural areas, cliffs

| Specification                  | Value  |  |
|--------------------------------|--|--|
| Туре                           | Digital Signal Boosters (without Antenna Feedback Cancellation)  |  |
| Frequency range                | 155 - 174 MHz  |  |
| Passband BW                    | 2MHz max   |  |
| Internal Duplexer              | No   |  |
| Number of Channels             | Channel Selective (90KHz, 45KHz, 30KHz, 20KHz, and 15KHz BW), 1 to 32  |  |
| Gain, maximum                  | 80 dB  |  |
| Passband ripple                | +/- 2.0 dB   |  |
| Gain, manual control           | 28dB range, digitally controlled in 1dB steps  |  |
| Antenna isolation              | Max Gain + 15 dB   |  |
| Composite output power, DL     | +24 dBm composite  |  |
| Composite output power, UL     | +24 dBm composite  |  |
| IM and spurious generation     | <-13 dBm   |  |
| Simplex option                 | Configurable   |  |
| Noise figure                   | 9.0 dB max at maximum gain   |  |
| Impedance                      | 50 Ω   |  |
| Group delay                    | Channel Selective 90KHz, 14µS  |  |
|                                | Channel Selective 45KHz, 23µS  |  |
|                                | Channel Selective 30KHz, 32µS  |  |
|                                | Channel Selective 20KHz, 45µS  |  |
|                                | Channel Selective 15KHz, 55μS  |  |
| Maximum input power, no damage | 0 dBm (UL)   |  |
|                                | -35dBm (DL)  |  |
| Connectors                     | N(f) as standard   |  |
| RF Input/Output impedance      | 50Ω  |  |
| Uplink squelch function        | Yes, user selectable, to avoid UL noise when no carriers present, by time slot and by channel (Channel Selective model only) |  |
| Self diagnostic platform       | Microprocessor based   |  |

# DOC BD342.00 • 06042019 • DM Fiplex is a registered trademark of Fiplex Communications, Inc . Fiplex Communications, Inc. reserves the right to change specifications without prior notice.

# VHF DIGITAL SIGNAL BOOSTERS 155 - 174 MHz

# DH124-040 DH124-041

| Specification                     | Value   |  |
|-----------------------------------|---|--|
| Alarms                            | Yes, amplifiers status, power amplifiers status, power supply failure, battery backup failure, temperature, AGC, RF overload, poor antenna isolation. |  |
| Local management and supervising  | Local access via USB and Ethernet (web browser)   |  |
| Remote management and supervising | Remote access via Ethernet. Wireless modem, SNMP as optional.   |  |
| RoHS compliance                   | Yes   |  |
| Power Supply                      | see table   |  |
| Power Consumption                 | 170 W   |  |
| Housing                           | IP67 / NEMA4X   |  |
| Temperature range                 | -13° to 131° F • -25° to +55° C   |  |
| Cooling                           | Natural convection  |  |
| Dimension                         | 20.2 x 18.2 x 9 inches • 514 x 462 x 230 mm   |  |
| Weight                            | 55 lbs • 25 kg  |  |
| Mounting                          | Wall mounting   |  |
| MTBF                              | <50.000 hours   |  |

| Product Code | Class              | Config. | Composite Output Power | Power Supply Option |
|--------------|--------------------|---------|------------------------|---------------------|
| DH124-040    | A - 32 channels UL | 01      | + 24dBm per band       | AC                  |
|              | 32 channels DL     |         |                        |                     |
| DH124-041    | A - 32 channels UL | 01      | + 24dBm per band       | DC                  |
|              | 32 channels DL     |         |                        |                     |

WARNING: This is NOT a CONSUMER device. It is designed for installation by FCC LICENSEES and QUALIFIED INSTALLERS. You MUST have an FCC LICENCE or express consent of an FCC Licensee to operate this device. Unauthorized use may result in significant forfeiture penalties, including penalties in excess of \$100,000 for each continuing violation.

